



	Model	ABCDEF3000-11				ABCDEF3000-22			
	Topology	True On-line, Double-Conversion, IGBT Design, Internal Isolation Transformer							
INPUT	Voltage (VAC)	100	115	120	200	208	220	230	240
	Voltage Range (VAC)	70-115	81-132	84-138	140-230	146-239	154-253	161-264	168-276
	Voltage Tolerance	+ 15% ~ -30% before switching to batteries							
	Frequency (Hz)	50/60							
	Frequency Tolerance	42 Hz to 69 Hz before switching to batteries							
	Input PF	> 0.95							
	Input Current THD	< 5.0%							
	Input Connection	Hardwired Standard; Line Cord Optional (Consult factory)							
Input Capacity	3240 VA				3240 VA				
OUTPUT	Capacity	3000VA/ 2700W							
	Voltage (VAC)	100	115	120	200	120 208 240	220	230	120 208 240
	Voltage Regulation	± 3.0% Max, ± 1.0% Normal							
	Output Voltage THD	< 3.0%							
	Power Factor	0.9							
	Step Load Response	± 4.0% for 50% step load change ± 6.0% for 100% step load change Return to ±3.0% of nominal within 3 cycles							
	Crest Factor	3:1							
	Frequency (Hz)	50/60							
	Frequency Regulation	± 0.1Hz							
	Overload	125% for 2 minutes 150% for 30 seconds 300% for 500ms							
	Efficiency	AC-AC >85.0%				AC-AC >85.0%			
		DC-AC >77.0%				DC-AC >76.0%			
Common Mode Noise	< 0.5 VRMS								
Output Connection	Hardwired Standard; Output Receptacles Optional (Consult factory)								
BYPASS	Input Voltage (VAC)	100	115	120	200	208	220	230	240
	Output Voltage (VAC)	100	115	120	200	120 208 240	220	230	120 208 240
	Transformer Voltage Regulation	± 3.0%							
	Overload	125% for 10 minutes 150% for 500ms 1000% for 1 cycle							
	Efficiency	> 95.0%							

BATTERY	Voltage (VDC)	96.0, nominal 109.2, float	
	Battery	12V, 34W flame retardant High Rate, Sealed Lead-Acid	
	Quantity	16	
	Charge Current (ADC)	3.0	
	Backup Time (min)	> 12.0	
	Recharge Time	8 Hours to 90%	
ENVIRONMENT	Temperature (°C)	0 to 40, operating -20 to 60, transit	
	Altitude (m)	2,000, operating 12,000, transit	
	Humidity	5.0% to 90.0%, non condensing	
	Audible (dBA)	50-55 @ 1m from front of unit	
	Heat Dissipation (BTU/hr)	1626	
AGENCIES	EMC	FCC Part 15J Class A EN 55022 Class A/ CISPR 22 EN 50091-2 IEC 61000-3-2	
	Safety Agencies	UL1778 4 th Ed. cUL to CSA22.2 No.107.1 CE (-22 only): IEC62040, w/CB report and cert IEC61000-4-2, Electrostatic Discharge IEC61000-4-3, Radiated Electromagnetic Field Immunity IEC61000-4-4, Electrical Fast Transient/ Burst Immunity IEC61000-4-5, Surge Immunity IEC61000-4-6, Immunity to Conducted Radio Frequency Disturbances IEC61000-4-8, Power Frequency Magnetic Field Immunity IEC61000-4-11, Voltage Dips, Short Interruptions, and Voltage Variations	
	RoHS	All units are RoHS compliant	
OTHER	Communication	RS-232 USB DB-9 Dry Contacts Internal SNMP Adapter (option)	
	Unit Weight	-11 Models 294 lbs. / 132 kg. -22 Models 300 lbs. / 135 kg.	
	Shipping Weight	-11 Models 389 lbs. / 175 kg. -22 Models 395 lbs. / 178 kg.	
	Plug & Receptacle*	L5-30P (2)5-20R (1)L5-30R	208 VAC Input L6-30P (2)5-20R (1)L6-30R 240 VAC Input L6-20P (2)5-20R (1)L6-20R

*Hardwired unit is standard. Plug & Receptacle is optional. Contact factory for part numbers.

NOISE REJECTION-ISOLATION: With unit under power and an ANSI/IEEE C62.41 Cat. A pulse applied either normal or common mode at the input, the noise output voltage will be less than 10V normal mode and less than 0.5V common mode in all four quadrants (CM-NM, NM-NM, CM-CM, NM-CM).

SURGE VOLTAGE WITHSTAND CAPABILITY: Tested under power to ANSI/IEEE C62.41 Cat. A & B (formerly IEEE587-1980). Cat. A - 6000V @ 200 amps, 0.5 usec risetime, 100 kHz decay, Cat. B - 6000V @ 500 amps, 0.5 usec risetime, 100 kHz decay.

ABCDEF3000-11 Compatible External (Extended Run) Battery Cabinets:

Model: D9632-11 Description: 4 Pack (32 Batt) Extended Run Battery Cabinet
 Model: D9648-11 Description: 6 Pack (48 Batt) Extended Run Battery Cabinet

ABCDEF3000-11 TYPICAL RUN-TIMES (MINS)				
	25% (675 W)	50% (1350 W)	75% (2025 W)	100% (2700 W)
Internal Batteries Only	40	24	17	12
Internal + 1) D9632-11	170	100	70	55
Internal + 2) D9632-11	325	200	140	110
Internal + 3) D9632-11	550	325	225	170
Internal + 4) D9632-11	>12 Hrs	450	310	230
Internal + 5) D9632-11	>12 Hrs	600	400	300
Internal + 1) D9648-11	250	150	100	80
Internal + 2) D9648-11	550	325	220	160
Internal + 3) D9648-11	>12 Hrs	525	350	250
Internal + 4) D9648-11	>12 Hrs	>12 Hrs	525	375
Internal + 5) D9648-11	>12 Hrs	>12 Hrs	700	525

Notes: Run-Times are based on new fully charged batteries at 25 deg C ambient.

ABCDEF3000-22 Compatible External (Extended Run) Battery Cabinets:

Model: D9632-22 Description: 4 Pack (32 Batt) Extended Run Battery Cabinet
 Model: D9648-22 Description: 6 Pack (48 Batt) Extended Run Battery Cabinet

ABCDEF3000-22 TYPICAL RUN-TIMES (MINS)				
	25% (675 W)	50% (1350 W)	75% (2025 W)	100% (2700 W)
Internal Batteries Only	35	23	15	12
Internal + 1) D9632-22	160	100	70	55
Internal + 2) D9632-22	325	200	140	110
Internal + 3) D9632-22	500	300	210	165
Internal + 4) D9632-22	>12 Hrs	425	300	230
Internal + 5) D9632-22	>12 Hrs	575	400	300
Internal + 1) D9648-22	230	150	100	80
Internal + 2) D9648-22	500	300	210	160
Internal + 3) D9648-22	>12 Hrs	500	350	270
Internal + 4) D9648-22	>12 Hrs	>12 Hrs	525	375
Internal + 5) D9648-22	>12 Hrs	>12 Hrs	675	500

Notes: Run-Times are based on new fully charged batteries at 25 deg C ambient.

Battery Life Disclaimer: POWERVAR's standard battery warranty applies only to UPS and UPM products which are continuously connected to AC mains power, except during utility power outages. Products which are regularly and intentionally disconnected from AC mains power will experience battery discharge/charge cycles potentially far more numerous than those for which the battery was designed. As a result, products used in such applications will experience substantially reduced battery life. For that reason, POWERVAR's standard battery warranty does not apply for applications in which the UPS or UPM product is regularly and intentionally disconnected from AC mains power. POWERVAR UPS and UPM products used in such applications shall receive a 90 day warranty on batteries.

Warranty/Support: POWERVAR warrants the electronics and transformers used in its uninterruptible power supplies to be free from defects in materials and workmanship for a period of three years from the date of shipment. Batteries are warranted for a period of two years from the date of shipment for standby use; 90 days for cyclic use. For North American service or support on any POWERVAR product, please contact POWERVAR Technical Support at (800) 369-7179 (in Illinois call (847-596-7000)). For service and support in EMEA, contact POWERVAR, Ltd. in the United Kingdom at +44 (0) 1793 553980. Or visit the POWERVAR website at www.powervar.com.

POWERVAR, Inc. - 1450 Lakeside Drive, Waukegan, IL 60085